

Functional Devices, Inc. 101 Commerce Drive, Sharpsville, IN 46068

Email: sales@functionaldevices.com | Website: www.functionaldevices.com Toll Free: (800) 888-5538 Office: (765) 883-5538 | Fax: (765) 883-7505

AC POWER SUPPLIES: 120 VAC TO 24 VAC

PSC40AB10

Single 40 VA Power Supply, 120 Vac to 24 Vac, 10 Amp Main Breaker, Metal Enclosure

PSC100AB10

Single 100 VA Power Supply, 120 Vac to 24 Vac, 10 Amp Main Breaker, Metal Enclosure















* Move internal jumper to "HOT" position if you wish outlets to always be hot otherwise outlets will be switched by main breaker.







SPECIFICATIONS

Transformer: One 40 VA Split-Bobbin,

Inherently Limited (PSC40AB10) One 100 VA Split-Bobbin, Circuit

Breaker (PSC100AB10)

Primary: 120 Vac

Secondary: 24 Vac, w/ LED Indicator

Frequency: 50/60 Hz

24 Vac ON/OFF: On / Off Switch & Breaker

Main Breaker ON/OFF: Switch / Breaker (10 Amp)

(Kills power to entire unit: Outlets, Aux. Output, & Transformer)*

Total Combined Output 9A Mounting: Mounting plate included (as shown)

Max. Ambient Temperature: 40° C

Approvals: Class 2 (UL Approved UL5085-3), UL916,

C-UL, CE, RoHS

Dimensions: 6.250" H x 5.620" W x 3.900" D Origin: Made of US and non-US parts

- To order without enclosure, see PSB40AB10
- •To order without enclosure, see PSB100AB10.